



扫码关注

Data Sheet

NC6000A/NC8000A Series AWGN Noise Generator



NC6000A/NC8000A Series AWGN Noise Generator

The **NC6000A** and **NC8000A** Series instruments are designed for general-purpose noise applications on the bench, or in a rack test station. The manual controls make it simple to operate and reduce test set up time. The standard output power NC6000A is typically used for BER, and SNR applications, while the high power NC8000A is a good candidate for signal jamming. Each instrument contains a precision noise source that delivers repeatable, symmetrical white Gaussian noise and is integrated with an amplifier, attenuator, and power supply. Noisecom will modify base units for specific customer needs. For pricing and availability, consult the factory.

General Specifications

- Output White Gaussian noise
- Attenuator range 0 to 10 dB in 1 dB steps
- Impedance 50 Ohms
- Typical VSWR 1.5:1
- Standard connector SMA female (K female for NC6226)
- Dimensions:
(NC6000A) 8.5 in. wide x 5 in. high x 12.25 in. deep
(NC8000A) 17 in. wide x 5.25 in. high x 13 in. deep
- Power requirements are 120 VAC, 60 Hz, at 500 mA for the NC6000A, 1500 mA for the NC8000A
- Operating temperature -10° to + 60°C



Applications

- BER Testing
- Military Jamming
- "K" Band Capability
- CATV Testing
- Video Testing
- General Purpose



Specifications

NC6000A/NC8000A Series

NC6000A		Output Characteristics			
Model	Frequency Band	Power (dBm)	PSD dBm/Hz	Flatness (dB)	$\mu\text{V}/\text{root (Hz)}$
NC6105A	10 Hz-10 MHz	+13	-57	± 0.75	316
NC6108A	100 Hz-500 MHz	+10	-77	± 1.5	31.6
NC6110A	100 Hz-1.5 GHz	+10	-82	± 2.0	18.2
NC6111A	1 GHz-2 GHz	+10	-80	± 2.0	22.4
NC6112A	1 MHz-2 GHz	0	-93	± 2.5	5.01
NC6113A	1 MHz-3 GHz	0	-95	± 2.5	5.01
NC6116A	10 MHz-6 GHz	-10	-107	± 2.5	0.98
NC6128A	10 MHz-10 GHz	-17	-117	± 3.5	0.32
NC6218A	2 GHz-18 GHz	-20	-122	± 3.0	0.18
NC6226A	2 GHz-26.5 GHz	-20	-124	± 3.0	0.14

NC8000A

Model	Frequency Band	Power (dBm)	PSD dBm/Hz	Flatness (dB)
NC8111A*	5 MHz-1 GHz	+30	-60	± 2.5
NC8112A	1GHz -2 GHz	+30	-60	± 2.5

*High power units have a reduced crest factor.

Options

Option Number	Description
NC6/NC8opt01	100 dB attenuator in 10 dB steps*
NC6/NC8opt02	110 dB attenuator in 1 dB steps (two attenuators)**
NC6/NC8opt03	Line power 230 VAC, 50 Hz
NC6/NC8opt04	Combiner for input signal (6 dB loss in noise and signal paths)
NC6opt06	19 in. Rack mount (NC6000 only) 17 in. wide by 3.5 in. high by 13 in. deep
NC6/NC8opt07	N female output connector
NC6/NC8opt08	BNC female output connector
NC6/NC8opt09	75-ohm output impedance (6 dB loss)
NC6/NC8opt10	Additional 1 dB attenuator in 0.1 dB steps***
NC6/NC8opt11	Custom frequency, power, or flatness requirement****

*60 dB for NC6218A, and NC6226A

**69 dB for NC6218A, NC6226A

***N/A for NC6226A

****Consult factory for pricing and availability



NC6000 with a rack mount.



NC8000 Noise Generator.



Wireless Telecom Group Inc.
 25 Eastmans Rd
 Parsippany, NJ
 United States
 Tel: +1 973 386 9696
 Fax: +1 973 386 9191
 noisecom.com

© Copyright 2022
 All rights reserved.

N/N/C6000/0522/EN
 Note: Specifications, terms and conditions
 are subject to change without prior notice.



Noisecom是WTG (Wireless Telecom Group) 集团旗下全资子公司，总部坐落于新泽西州帕西帕尼，位于纽约市大都会区。

作为全球领先的射频、微波噪声源设计和制造商，其产品广泛应用于信号阻塞、加损、计量标校、抖动噪声加载、接收机性能等测试领域。

Noisecom拥有全球销售和服务办事处网络，致力于为用户提供卓越的产品服务和支持。

中国区(含香港)代理
南京舜特科通信技术有限公司

电话: 025-52635773

邮箱: sales@sainty-tech.com

网址: www.sainty-tech.com

www.noisecom.com

地址: 南京市江宁区胜利路89号紫金研创中心3号楼801