


Performance

- Frequency: 2~8.5GHz
- Typical Signal Gain: 26dB
- Typical Pout: 33dBm @28V
- Typical Idq: 0.25A
- Bias: 28V, -1.8V (Typ.)
- Mode: CW
- Technology: 0.2um HEMT
- Size: 2.6*1.9mm*0.08mm

Function Diagram




Electrical Specifications (Vd=28V, Idq=0.25A, F: 2~8.5GHz, CW)


Symbol	Parameter	Min	Typical	Max	Unit
G	Small Signal Gain	-	26	-	dB
Gp	Power Gain	-	21	-	dB
Pout	Saturated Power	-	33	-	dBm
PAE	Power Added Efficiency	-	30	-	%

Test Curves


Small Signal Gain vs. Freq




Input VSWR vs. Freq




Output Power vs. Freq




PAE vs. Freq



Drain Current vs. Freq




Grid Current vs. Freq







Absolute Max Ratings (TA=25°C)

Symbol	Parameter	Value	Remark
Vd	Drain Voltage	32V	
Id	Drain Current	0.6A	
Pd	DC Power	15W	
Pin	Input Power	18dBm	
Tch	Channel Temperature	225°C	
Tm	Mounting Temperature	310°C	1min, N2 Protection
Tstg	Storage Temperature	-55~175°C	

Exceeding any one or combination of these limits may cause permanent damage.



Pads Definition

Pin	Description	Equivalent Circuit
RFin	RF Signal input, connect to 50ohm system, block capacitor is needed if there's external DC applied on this pad	
RFout	RF Signal output, connect to 50ohm system, no need block capacitor	
VG	Amp gate bias, external 150pF, 1000pF capacitor is needed	
VD	Amp drain bias, external 150pF, 1000pF capacitor is needed	
GND	Bottom must connect to RF and DC ground	